

CARBON MONOXIDE AND SMOKE DETECTION APPARATUS

Related Application

This is a continuation application of U.S. patent application Serial
Number 09/058,467, filed April 9, 1998, entitled "CARBON MONOXIDE AND
SMOKE DETECTION APPARATUS", which claims priority from provisional
U.S. patent application Serial No. 60/055,009, entitled "SMOKE AND GAS
DETECTORS," filed August 7, 1997, the subject matter and entire writings of
which are incorporated herein by reference.

Field Of The Invention

The present invention relates generally to detecting a condition in
the environment. Particularly, the invention pertains to apparatus and methods to
detect the presence of carbon monoxide and smoke in the atmosphere.

Background

The threat of carbon monoxide poisoning has increased dramatically
in the past decade. Carbon monoxide is a colorless, odorless, tasteless gas, making
it virtually impossible to detect its presence. Carbon monoxide can be produced by
various fuel burning appliances, such as, fuel fired furnaces, gas hot water heaters,
gas stoves, gas dryers, space heaters, charcoal grills, fireplaces, vehicles, lawn
mowers, or snow blowers. Once present, this gas circulates freely throughout a
building, such as a home. If this gas is not ventilated properly, carbon monoxide
poisoning may result.

Carbon monoxide inhibits the blood's ability to carry oxygen to
body tissue, including vital organs such as the heart and brain. When carbon
monoxide is inhaled, it combines with oxygen-carrying hemoglobin of the blood to
form carboxyhemoglobin. Once combined with the hemoglobin, the hemoglobin is
no longer available for transporting oxygen. The amount of carboxyhemoglobin
that builds up is a factor of the concentration of the gas being inhaled and the
duration of the exposure.

Carbon monoxide can act in the body in high concentrations, or slowly over a long period of time. Because it takes several hours to remove carbon monoxide from the body of a person, concentrations of carbon monoxide can gradually build up in the blood causing headaches, fatigue, dizziness, nausea, burning eyes, or unconsciousness.

Devices for sensing carbon monoxide and triggering an alarm in the presence of excess concentrations of carbon monoxide are presently available. These CO detectors typically employ a solid state sensor which purges itself and resamples for carbon monoxide on a periodic basis. However, conventional carbon monoxide detectors usually do not account for low levels of the carbon monoxide gas over long periods of time. Known detectors of this type are intended to be plunged into AC receptacles and are not battery powered.

Other types of known CO detectors utilize biomimetic sensors. Such devices are battery powered and detect changes in opacity of the biomimetic material.

In addition to being generated by operation of various products, carbon monoxide is produced along with smoke by fire. Fire detectors operate on different principles than do carbon monoxide detectors. Known fire detectors respond to heat, flame or smoke.

The range of presently available products includes separate carbon monoxide and fire detectors. It would be useful if the sensing characteristics of these separate units could be incorporated into a single, easy to use, easily installed, multi-mode product.

Summary Of The Invention

In view of the above, the present invention provides methods and apparatus for monitoring the presence and changes in the concentration of carbon monoxide. A detector that embodies the invention may also detect the presence of smoke.

In one aspect, a combined smoke and CO detector is battery operated. The detector carries a carbon monoxide sensor that is sealed until it is to be used by a consumer.

5 The CO sensor is carried within a housing and is not user replaceable. Removable tape seals the CO sensor until the detector is put into service. The sealing tape is applied when the carbon monoxide sensor is assembled. When a user places the detector into service the tape is removed thereby exposing the CO sensor to the ambient air.

10 An ionization-type smoke sensor is also carried within the housing. Both sensors are coupled to a programmed processor. The detector is energized by a single replaceable battery.

15 The process, in response to signals from the sensors, can produce an audible alarm indicative of the presence of carbon monoxide. A different audible alarm, for example in accordance with NFPA standard No. 72, can be produced to indicate the presence of smoke. In one aspect, if both carbon monoxide and smoke are present, the processor can go immediately unto a fire alarm indicating state.

In yet another aspect, a test circuit can be provided. For example, activating the test button can test each sensor sequentially. In this instance, appropriate audible alarms can be alternately produced.

20 In one aspect, a smoke determination can be made independently of a CO determination. The smoke determination can predominate and force the generation of visible and audible alarms.

25 Visual indicators of an alarm condition provide visual feedback to users. In one aspect, a symbol indicates if smoke is present and can be illuminated in the presence of detected levels thereof. Similarly, in the presence of pre-selected levels of carbon monoxide, a visual symbol indicative thereof can be illuminated. The visual indicators can be sequentially illuminated during a test sequence.

30 In yet another aspect, the detector and both of the sensors can be energized by a single battery. For example, a removable battery door can be provided. If the door is mounted in a user accessible side of the detector it will be

possible to replace the battery with removing the detector from its mounted location.

The detector periodically measures the output of a CO sensor. The detector subtracts each sampled CO sensor output from the previous sampled sensor output. The difference of between the successive sampled sensor outputs are summed. The detector unit determines the rate of change of the sampled sensor outputs to determine the level of CO in the atmosphere. The detector can actuate an alarm when a predetermined CO condition is detected.

The methods and applications of the present invention provide a highly efficient and low cost detector that is capable of detecting the presence of carbon monoxide at an early stage to allow persons to evacuate the area. The detector can also detect low concentrations of carbon monoxide over long periods of time. The detector unit may also detect the presence of smoke.

The invention, together with further attendant advantages, will best be understood by reference to the following detailed description of the presently preferred embodiments of the invention, taken in conjunction with the accompanying drawings. It is to be understood that both the foregoing general description and the following detailed description are exemplary and explanatory and are intended to provide further explanation of the invention as claimed.

Brief Description of The Drawings

FIG. 1 is a block diagram of a combined carbon monoxide and smoke detector;

FIG. 1a is a plan view of the detector;

FIG. 2 is a block diagram illustrating arrangement of FIGs. 2-1 .. 2-4 which taken together are a schematic diagram of the detector of FIG. 1;

FIG. 2a-1 and 2a-2 taken together are a flow diagram of a main routine of the detector of FIG. 1;

FIG. 3 is a flow diagram of a SUB-ROUTINE OF THE MAIN ROUTINE of FIGs. 2-a-1, -2;

FIG. 4 is a flow diagram of a POWER-UP sub-routine of the main routine of FIG. 2a-1, -2;

FIG. 5 is a flow diagram of a WAKE sub-routine of the main routine of FIG. 2a-1, -2;

5 FIG. 6 is a flow diagram of a RES1 sub-routine of the main routine of FIG. 2a-1, -2;

FIG. 7 is a flow diagram of a RESET sub-routine and a RESET1 sub-routine of the main routine of FIG. 2a-1, -2;

10 FIG. 8 is a flow diagram of a LOOP sub-routine of the main routine of FIG. 2a-1, -2;

FIG. 9 is a flow diagram of a NEG1 sub-routine of the main routine of FIG. 2a-1, -2;

FIG. 10 is a flow diagram of a TESTR sub-routine of the main routine of FIG. 2a-1, -2;

15 FIG. 11 is a flow diagram of a SMOKE CHECK sub-routine of the main routine of FIG. 2a-1, -2;

FIG. 12 is a flow diagram of a TEST sub-routine of the main routine of FIG. 2a-1, -2;

20 FIG. 13 is a block diagram of an alternate detector, carbon monoxide;

FIG. 14 is a schematic diagram of the detector of FIG. 13;

FIG. 15 is a flow diagram illustrating the general operation of the detector of FIG. 13;

25 FIG. 16 is a flow diagram of a main routine of the detector of FIG. 13;

FIG. 17 is a flow diagram of a WAKE sub-routine of the main routine of FIG. 16;

FIG. 18 is a flow diagram of a TESTER sub-routine and a BYE1 sub-routine of the main routine of FIG. 16;

FIG. 19 is a flow diagram of an ACR1 sub-routine of the main routine of FIG. 16;

FIG. 20 is a flow diagram of a RESET sub-routine and a RESET1 sub-routine of the main routine of FIG. 16;

5 FIG. 21 is a flow diagram of a LOOP sub-routine of the main routine of FIG. 16;

FIG. 22 is a flow diagram of a NEG1 sub-routine of the main routine of FIG. 16;

10 FIG. 23 is a flow diagram of a TEST sub-routine of the main routine of FIG. 16;

FIG. 24 is a flow diagram of a BAT1 sub-routine of the main routine of FIG. 16;

FIG. 25 is a flow diagram of an INSPECT sub-routine of the main routine of FIG. 16;

15 FIG. 26 is a flow diagram of a POS1 sub-routine, a ACC3 sub-routine, and ADJ1 sub-routine of the main routine of FIG. 16;

FIG. 27 is a flow diagram of an ACCUM sub-routine and a SET6 sub-routine of the main routine of FIG. 16;

20 FIG. 28 is a flow diagram of a CHKSP sub-routine of the main routine of FIG. 16;

FIG. 29 is a flow diagram of a SHOW sub-routine and a NOSHOWN sub-routine of the main routine of FIG. 16;

FIG. 30 is a flow diagram of a XMITR sub-routine of the main routine of FIG. 16;

25 FIG. 31 is a flow diagram of a TIME sub-routine and TIME 1 sub-routine of the main routine of FIG. 16;

FIG. 32 is a flow diagram of a DEL001 sub-routine, of the main routine of FIG. 16;

30 FIG. 33 is a flow diagram of a DEL225 sub-routine, and a DELPROG sub-routine of the main routine of FIG. 16;

of the main routine of FIG. 16;

FIG. 34 is a flow diagram of a CLRREG sub-routine of the main routine of FIG. 16; and

FIG. 35 is a flow diagram of a M16 sub-routine of the main routine of FIG. 16.

Detailed Description Of The Preferred Embodiments

Before explaining the present embodiments in detail, it should be noted that the invention is not limited in its application or use to the details of construction and arrangement of parts illustrated in the accompanying drawings and description, because the illustrative embodiments may be implemented or incorporated in other embodiments, variations and modifications, and may be practiced or carried out in various ways. Furthermore, unless otherwise indicated, the terms and expressions employed herein have been chosen for the purpose of describing the illustrative embodiments for the convenience of the reader and are not for the purpose of limitation.

Referring now to the drawings and particularly to FIG. 1, a block diagram of a preferred embodiment of a detector 50 is illustrated. The detector 50 is a battery powered, single station, self-contained smoke and carbon monoxide alarm detector. The detector 50 detects the presence and concentration of carbon monoxide in the atmosphere and provides a warning to indicate a hazardous condition of carbon monoxide. The detector 50 also detects the presence of smoke in the air and provides a warning to indicate the presence of smoke.

As shown in FIG. 1, the detector unit 50 includes a housing 50a, control circuitry 100, an ionization sensing chamber, electronic measurement and control circuitry 110, audible and visual indicators, power circuitry, test/silence circuitry, temperature compensation circuitry, reset circuitry, low voltage detection circuitry, test switch/hush circuitry, output circuitry, interconnect circuitry and oscillator circuitry. Although it is shown as being constructed with various types of independent and separate units or devices, the detector 50 may be implemented

utilizing one or more integrated or logic circuits, or a microprocessor which may be programmed to execute the operations or functions equivalent to those performed by the circuitry units shown. It is also contemplated that the detector can be carried out with any suitable hardware components and circuitry designs, computer programming, or a combination thereof.

FIG. 1a shows a front plan view of the housing of the detector unit 50. The housing includes a CO alarm indicator 50a, a smoke alarm indicator 50b, a low battery indicator 50c, and a service status visual indicator 50d. The housing also preferably includes a single test/silence button as further illustrated below.

With respect to FIGS. 1 and 2, the control circuitry 100 of the detector 50 includes a processing unit 102. As shown in FIG. 2, the processing unit 102 includes a Microchip PIC16C57, available from microchip. The processing unit 102 preferably has a 2MHz internal clock, Read Only Memory (ROM), Random Access Memory (RAM), and a plurality of input/output (I/O) pins. The processing unit 102 controls the overall operation of the detector unit 50 and processes information to determine a hazardous condition of carbon monoxide or smoke in the atmosphere. It will be understood that a variety of processing units or processors could be used without departing from the spirit and scope of the present invention.

The processing unit 102 preferably spends most of its time in a "sleep" mode in order to save power. While the processing unit 102 is in the "sleep" mode, the detector 50 typically consumes about 5 μ A of current. In the sleep mode, the internal clock of the processing unit 102 is disabled and the program counter is stopped.

The processing unit 102 can be "awakened" either by an external low level signal on pin 28 of the processing unit 102 or an internal reset initiated by an on-board watchdog timer. The watch dog timer is preferably used as an operational cycle clock to awaken the processing unit 102 about every 3 seconds to increment a time counter which requires about 2 μ A.

The processing unit 102 takes sensor samples about every 30 seconds, battery and built-in tests occur about every 10 minutes. In order to limit the current drain of the detector unit 50 below $15\text{ }\mu\text{A}$, the current used for sensor sampling cycle (which occurs once about every 30 seconds for approximately 25 ms) is usually kept to an average of about $5\text{--}6\text{ }\mu\text{A}$. Unless the detector unit 50 is taking a sensor sample, checking the battery, performing a built-in test, or preforming a user-initiated push-button test, the processing unit 102 will usually not be turned on for more than 25 ms before the processing unit 102 is put back to sleep.

The electronic measurement circuitry 110 preferably includes carbon monoxide detection circuitry 112, smoke detection circuitry 114, and smoke calibration circuitry 116. The carbon monoxide detection circuitry 112 monitors the presence or absence of carbon monoxide. When initially assembled a gas input port of the sensor 112 is covered by a removable protective tape 112a to prevent contamination. The tape 112a is removed by the user when the detector 50 is first activated.

As shown in FIG. 2, the carbon monoxide detection circuitry 112 includes resistors R16, R17, R33, and R34, a capacitor C5, a transistor Q2, and a biomimetic sensor S1. Preferably, the resistors R16, R17, R33 and R34, are about 100Ω , $330\text{K}\Omega$, $3.3\text{K}\Omega$ and $1\text{K}\Omega$, respectively, and the capacitor C5 is preferably about $0.022\text{ }\mu\text{F}$.

The sensor S1 of the carbon monoxide detection circuitry 112 is utilized to detect the presence or absence of carbon monoxide in the surrounding atmosphere. The sensor S1 includes an infrared IR LED, a sensing device and a photo diode. The sensing device S1 is preferably a passive component that requires no additional power for its operation. The sensor S1 is preferably a S30 model, manufactured by Quantum Group.

Temperature compensation circuitry or resistor/thermistor network 150 drives the IR LED of the sensor S1 and acts as a constant current source, eliminating variations in the light output of the sensor S1 which might otherwise be

imparted by changes in the battery voltage. The temperature compensation or circuitry 150 preferably includes resistors R18 and R20 and thermistor TH1. The resistors R18 and R20 are each preferably about 33Ω . When the ambient temperature varies, changes in the impedance of the thermistor TH1 adjusts the current supplied to the IR LED of the sensor S1, stabilizing the light output.

The light emitted (940 nm) by the IR LED is passed through the sensor and detected by the photo diode to provide a measure of the absorbency of the sensor. Because the sensor darkens when exposed to carbon monoxide, increased absorbency of the light energy of the LED can be utilized to detect the presence of carbon monoxide in localized atmospheric environments, such as, for example, inside homes, offices, etc. As carbon monoxide molecules are absorbed by the sensor, the sensor becomes more opaque. In the absence of the carbon monoxide in the atmosphere, the sensor releases previously absorbed molecules (if any present) becoming more transparent in the process.

The photo diode of the sensor S1, the capacitor C5, the resistor R16, and the processing unit 102 comprise a pseudo analog-to-digital (A/D) converter capable of measuring the absorbency of the sensor S1 with precision. The processing unit 102 receives and processes data on pin 9 supplied by the A/D conversion to determine the level of carbon monoxide present in the surrounding atmosphere. The pseudo A/D process measures the time needed to charge the capacitor C5 when the IR LED of the sensor S1 is enabled.

Initially, before the IR LED is enabled, any residual charge on the capacitor C5 is discharged to ground through the resistor R16 to pin 8 of the processing unit 102. Pin 8 of the processing unit 102 is then configured as a high impedance state input. The IR LED of the sensor device S1 is enabled through pin 13 of the processing unit 102 and a software timer in the processing unit 102 is started.

The processing unit 102 supplies a constant bias voltage level to the photo diode of the sensor S1. The voltage level is nearly the full value of the power supply voltage V_{cc} since, even at the highest level of photo diode current, the

voltage drop internal to the processing unit 102 (from supply pin 14 of the processing unit 102 to the output on pin 2) is minimal.

Because the charging current induced in the photo diode PD is nearly constant (over relatively short sampling intervals), the voltage on the capacitor C5 rises linearly over time. When the ramping voltage of the capacitor reaches about 0.85 Vcc, the software timer is terminated and a sampling time (ST) count is thereby obtained.

The absorbency of the sensor is sampled once about every 30 seconds. Each time the sensor absorbency is sampled, the sampling time value is compared with predetermined or programmable limits.

If the sensor is too light or too dark or sample time is too short or too long, a FAULT routine, as further described below, is initiated by the detector unit 50. Otherwise, the current value of the sample is compared with the value from the previous sample measurement, and the difference is stored in one of a plurality of storage registers. Subsequently, the storage registers are summed, and the value is placed in a sum register and also added to an alarm register.

The discrete sampling time values of the sensor S1 are measured over time by an the processor 102 as further described below. Since the light output for the LED of the sensor S1 is virtually constant over time, temperature, and voltage, the only mechanism by which the sampling time can change is relative absorbency of the sensor S1. When the concentration of carbon monoxide in the atmosphere surrounding the sensor increases, the sensor darkens and iterative sample times measured by the A/D converter lengthen or increase.

The sample time rate-of-change (dST/dt), is monitored by the processing unit 102, and its magnitude is used to trigger an "alarm" condition (i.e., a high level alarm) when the carbon monoxide levels present a hazardous condition. The sensor S1 also responds to various carbon monoxide concentrations in the manner consistent with the ULTO34 standard.

A status flag (i.e., ALARM FLAG) is set when the value in the alarm register reaches full scale (i.e., 255 decibel). At this time a high level alarm

is issued. When the carbon monoxide drops below about 50 ppm, the sensor begins to lighten and the values in the sum register become negative, causing a reduction in the value stored in the alarm register. If the value in the alarm register falls to about 48 or below, the sample, flag, and alarm registers in the high level alarm will be cleared, and the detector unit 50 will resume normal operation.

The A/D converter operation of the carbon monoxide detection circuitry 112 is verified by the processing unit 102 on power-up and about every 10 minutes thereafter (i.e., about every 20 sensor sampling cycles). The integrating capacitor C5 of the carbon monoxide detection circuitry 112 is discharged, and then allowed to charge by current supplied by pin 6 of the processing unit 102 through the A/D test resistor R17.

The software timer of the processing unit 102 executes a sample time measurements and the resultant value has to lie within program limits. This test checks for excessive leakage, shorting, or improper operation of the A/D measurement components. Any failure sets a fault flag and a fault condition is announced to notify the user.

The smoke detection circuitry 114 of the electronic measurement circuitry 110 detects the presence of smoke in the atmosphere. The smoke detection circuitry provides a signal to the processing unit 50 that generates a warning signal.

As shown in FIG. 2, the smoke detection circuitry 114 preferably includes a smoke detector D1, a smoke comparator unit U2, capacitors C3, C10, and C14, and resistors R2, R3, R4, R5, R28, and R30. The smoke comparator unit U2 is preferably a comparator such as Model No. SC41411PK available from Motorola (comparable to MC14467). The capacitors C3, C10, and C14 are each preferably about 0.1 μ F, and the resistors R2, R3, R4, R5, R28, and R30 are preferably about 1.5M Ω , 8.2K Ω , 1.5K Ω , 470K Ω , 1M Ω , and 33 Ω , respectively.

The smoke detector D1 preferably includes a single source dual ionization chamber C1 having an active chamber C1, a sensing electrode E1, and

an ion chamber I1. A 1.0 μCi maximum source of American 241 is employed in the ionization chamber.

5 The active chamber C1 is connected to ground by the parallel combination of the resistor R28 and the capacitor C10. The capacitor C10 provides transient protection for the active chamber C1, and the resistor R28 allows the active chamber C1 of the smoke detector D1 to be raised above ground by pin 18 of the processing unit 1d SW3 are closed, 3.3 volts is applied by pin 18 of the processing unit 102 to the resistor R28 to simulate about 40-50 pA MIC.

10 The sensing electrode E1 of the smoke detector D1 is connected to the non-inverting input (pin 15) of the smoke comparator unit U2. The connection of the sensing electrode, a very high impedance point, to the non-inverting input is preferably a flying connection to minimize leakage effects due to the presence of a printed circuit board.

15 Pins 14 and 16 of the smoke comparator unit U2 are connected together internally to a voltage follower of a non-inverting input of the smoke comparator unit U2 to provide an active guard output. This active guard reduces the effect of leakage between non-inverting input of the smoke comparator unit U2 and adjacent pins.

20 An alarm feedback pin (pin 1) of the smoke comparator unit U2 is monitored by the processing unit 102 to determine if a smoke condition exists. The feedback pin is preferably pulled to about 3.3 volts by a pull-up resistor R5 in a clean air condition. When smoke is present, the voltage across the dual chamber decreases and the voltage at the sensing electrode E1 increases.

25 The alarm feedback pin of the smoke comparator unit U2 will change to a low level state which is then read by the processing unit 102. The processing unit 102 will then go into a smoke alarm mode and turn on a smoke horn. The horn pattern consists of an active phase lasting about 0.5 seconds \pm 10% followed by an off-phase lasting about 0.5 seconds \pm 10%, for three successive active periods, which are then followed by an off-phase lasting about

1.5 seconds +/- 10%. This pattern is comparable to that specified by NFPA 72. Other patterns can be stored in the processor to use as needed.

5 The circuitry 114 establishes, using an alarm threshold established thereby, if enough smoke is present to warrant generating a smoke alarm. If so, the two state smoke alarm output signal goes from a high to a low which is indicative of a smoke alarm state. The processor 102 will in turn activate the visible and audible smoke alarms. This is completely independent of processing for the presence of CO.

10 The smoke calibration circuit 116 of the electronic measurement circuitry 110 preferably includes resistors R14, R32, and R36. The resistors R14, R32, and R36 are preferably 1M Ω , 1M Ω , and 1.5M Ω . The resistors R14, R32, and R36 preferably form a resistive divider to provide a reference voltage for the inverting input (pin 13) of the smoke comparator unit U2. The voltage division at the inverting input is designed so that under clean air conditions the two inputs are different to provide a nominal sensitivity of 67 pA MIC and that no alarm results.

15 On power-up of the detector 50, and about every 24 hours thereafter, proper smoke detector operation is verified by the processing unit 102. Initially, the resistor R28 of the smoke calibration circuitry 116 is raised above circuit ground by pin 18 of the processing unit 102. As a result, the voltage across the dual chamber of the detector D1 is lowered and the voltage at the sensing electrode E1 is raised.

20 The processing unit 102 applies about 3.3 volts to the resistor R28 to simulate about 40-50 pA MIC. The processing unit 102 then monitors the output of the smoke comparator U2 about every 10 seconds or less. Any failure of the smoke comparator U2 sets the fault flag and a fault condition is annunciated to notify the user.

25 A manual test mode is also provided for by the detector unit 50. This test mode is activated by the user, who simply pushes a test/silence button on the face of the detector unit until a horn chirp is issued and a yellow service LED flashes. Once the test mode is entered, the processing unit 102 applies 3.3 volts to

30

the resistor R28 of the smoke detection circuitry 114 to simulate about a 40-50 pA MIC. The processing unit 102 then monitors the output of the smoke comparator unit U2 Every 10 seconds or less until it is pulled low, which signifies a smoke condition. Any failure sets a fault flag and a fault condition is annunciated to
5 notify the user, and the carbon monoxide test is terminated.

If the output of the smoke comparator unit U2 is at a low level state before timing out, the processing unit 102 will emit one cycle of the smoke alarm pattern. If the detector unit 50 passes, the processing unit 102 pauses for about one
10 second to separate smoke and carbon monoxide tests. Then each green or yellow flash of a power LED depending on the battery status is preceded by a sensor sample cycle. Each of these samples is taken with pin 6 of the processing unit 102 configured as an input pulled to ground, stealing current through the resistor R33 of the carbon monoxide detection circuitry 112 which is normally supplied by pin
13 of the processing unit 102 to the base of transistor Q2. This activity "starves"
15 the respective LED, reducing the light admitted through the sensor, and effectively simulates a carbon monoxide exposure, filling the alarm register with about 3 to 5 sample cycles. A successful manual test results in a self-induced high level alarm state which is enabled for two cycles of the alarm pattern (i.e., on for 1.5 seconds and off for 1.5 seconds) indicating that the detector unit 50 is operating properly.

The audio and visual indicators 120 of the detector 50 are used in
20 conjunction with various self-tests and user-initiated tests to indicate when the detector unit 50 is operating normally or has a problem which requires service. The audio and visual indicators 120 also alert persons nearby when smoke and carbon monoxide concentrations are unhealthy or dangerous. The audio and visual
25 indicators 120 include carbon monoxide alarm indicator circuitry 122, smoke alarm indicator circuitry 124, horn driving circuitry 126, service indicator circuitry 128, and power/low battery indicator circuitry 129.

The carbon monoxide alarm indicator circuitry 122 of the audio and
visual indicators 120 preferably includes an indicator light LED2 and resistor R12.
30 The light emitting diode LED2 is preferably a red light emitting diode (LED), and

the resistor R12 is about 180 Ω . The carbon monoxide alarm indicator circuitry 112 is electrically coupled to pin 23 of the processing unit 102. The processing unit 102 activates the indicator light LED2 by pulling pin 23 to a low level state to provide a current path (typically, about 8 mA) from the power source through the indicator light LED2 and the current limiting resistor R12 to ground.

The smoke alarm indicator circuitry 124 of the audio and visual indicators 120 preferably includes an indicator light LED3 and a resistor R13. The indicator light LED3 is preferably a red light emitting diode (LED), and the resistor R13 is about 180 Ω . The smoke alarm indicator circuitry 124 is electrically coupled to pin 22 of the processing unit 102. The processing unit 102 activates the indicator light LED3 by pulling pin 22 to a low level state to provide a current path (typically, about 8 mA) from the power source through the indicator light LED3 and current limiting resistor R13 to ground.

The horn driving circuitry 126 of the audio and visual indicators 120 preferably includes a power oscillator U4, a piezoelectric alarm H1, resistors R19, R25, R37 and R38, and transistor Q4. The power oscillator U4 is preferably a MC14049VBCP available from Motorola is a known type used with smoke detectors. The resistors R19, R25, R37, and R38 are preferably about 1.5M Ω , 1.5M Ω , 1K Ω , and 1K Ω , respectively, the capacitor C7 is preferably about 0.0022 μ F.

The piezoelectric alarm H1 is driven by the power oscillator U4. Pin 2 of the piezoelectric alarm allows the power oscillator to resonate at a particular frequency, preferably within a range of about 3.5 kHz. In order to turn the piezoelectric alarm H1 on, the processing unit 102 sets output pin 11 to a high level state, putting the transistor Q4 into saturation, effectively connecting pin 8 of the power oscillator U4 directly to ground.

In operation, the detector unit 50 has a special alarm silencing function that can be initiated by the user to silence the alarm. This function is activated by pressing a test/silence button on the detector unit 50. When the detector is in a smoke alarm state, pressing the button will put the detector unit into

a silence mode. This mode will silence the horn for about 8 minutes. During this time, the light indicator LED3 of the smoke alarm indicator circuitry 124 will remain on. Pressing the test/reset button again while in silence mode, will reset a silence interval timer.

5 When in silence mode, the processing unit 102 desensitizes the ion chamber I1 by turning on the transistor Q5 of the hush/test circuitry 130, pulling the ion chamber to ground. Increasing levels of smoke will kick the processing unit 102 out of hush mode and continue with a smoke alarm condition.

10 When the detector is in a high level carbon monoxide alarm state, pressing the test/reset button will silence the horn for about 4 minutes. However, the light indicator LED2 of the carbon monoxide indicator circuitry 122 will remain on. The high level carbon monoxide alarm can be silenced only one time.

15 The power circuitry 130 of the detector unit 50 provides power to the various components of the detector unit 50. The power circuitry 130 includes a power supply and filter circuitry 132, reverse bias protection circuitry 134, and voltage regulator and filter circuitry 136. The power supply and filter circuitry 132 preferably includes a 9 volt battery B1 and a capacitor C2. Preferably, the battery B1 supplies power (i.e., about 8.4 volts) to the smoke comparator unit U2 and other associated circuitry. The battery is preferably a 9 volt alkaline type and the
20 capacitor C2 is about 0.1 μ F.

25 The voltage regulator and filter circuitry 136 of the power circuitry 130 preferably includes a voltage regulator U1, and capacitors C8 and C9. The voltage regulator U1 supplies a regulated 3.3 VDC to the processing unit 102 and its associated circuitry. The 3.3 volt level minimizes overall current drain in the detector unit, which is typically about 5-7 μ A. The voltage regulator U1 is preferably a Seiko S81233SG and the capacitors C8 and C9 are about 2.2 μ F and 0.1 μ F, respectively.

30 The reset circuitry 160 of the detector 50 insures proper reset of the processing unit 102 when the battery B1 is removed by discharging any capacitance on the output of voltage regulator U1. The reset circuit 160 of the

detector unit 50 preferably includes resistors R26, R27, R31, and R40, a capacitor C13 and a transistor Q3. The resistors R26, R27, R31, and R40 are preferably about 3.9K Ω , 10M Ω , 33K Ω , and 10M Ω , respectively, the capacitor C13 is about 0.1 μ F.

5 The reverse bias protection circuitry 134 of the power circuitry 130 provides protection for the circuitry of the detector unit 50 when the battery is installed improperly. The reverse bias protection circuitry 134 preferably includes a diode D5 and a resistor R35. The diode D5 of the reverse bias protection circuitry 134 prevents any damaging current flow through the voltage regulator U1
10 and the capacities C2, C8, and C9 if the battery is installed backwards. The resistor R35 is about 1K Ω .

 The resistor R35 of the reverse bias protection circuitry 134 limits current through a voltage detector U3 to a non-damaging level when the battery B1 is installed backwards, but is not large enough to substantially effect the level of
15 the battery voltage at the input (pin 2) of the voltage detector U3. The quiescent current drain through the voltage detector U3 is typically about 1 μ A, creating a voltage drop across the resistor R32 of only about 0.001 V_{dc}.

 About once every 10 minutes or every 20 operation cycles, the battery B1 is tested to insure it retains sufficient capacity to sustain operation after
20 a low battery condition is detected as specified by UL2034 standards. During this test, the processing unit 102 enables the IR LED of the sensor S1 for 10mS (which consumes about 20 mA) to load the battery for an accurate measurement.

 Before turning the IR LED off, the processing unit 102 samples the state of pin 1 of the voltage detector U3. When the battery level under load
25 exceeds 7.5 V_{dc} (the trip point of the voltage detector U3), the resistor R23 pulls up the open collector output (pin 1) of the voltage detector U3 to 3.3 volts. As a result, a high logic level is detected by pin 16 of the processing unit 102, which indicates the presence of a sufficient battery level. On the other hand, if the battery level under load is less than 7.5 V_{dc}, the open collector output of the voltage
30 detector U3 will be pulled to ground, causing pin 16 of the processing unit 102 to

detect a low logic level. In this case, the processing unit 102 sets a LOW BATTERY flag and indicates this condition to the user.

FIGS. 2a-1, 2a-2 taken together illustrate as, a flow diagram a general overview of the operations carried out by the detector 50. As shown in
5 FIG. 2a-1, after the detector 50 is awakened at block 250a or the detector 50 is powered up at block 250b, the detector 50 initializes a watchdog timer and initializes one or more ports at block 250c. At block 250d, the detector 50 determines whether it was just powered up.

10 If the detector 50 was just powered up, it sets a power-up delay at block 250e. At block 250f, the detector 50 initializes one or more counters, clears one or more sample registers, clears one or more flag registers, and clears the alarm register. The detector 50 then obtains an initial sensor count at block 250g and then goes into the sleep mode at block 250h.

15 If the detector 50 was not just powered up at block 250d, it will determine whether there is a smoke alarm condition at block 250i (based on a binary, low, output signal for comparator U2). If there is a smoke alarm condition, the detector 50 will flash the LED3 of the smoke indicator circuitry 124 and sound the smoke horn pattern at 250j. The process then proceeds to block 250k as further described below.

20 If a smoke alarm condition is not detected at block 250i, the detector 50 will determine whether a manual test has been initiated at block 250k. If a manual test has been initiated, the detector 50 will perform the manual test and then go into the sleep mode at block 250h.

25 If a manual test has not been initiated at block 250k, the detector 50 determines whether to perform a 30 second CO sample at block 250l. If the detector 50 does not have to obtain a 30 second sample, it will go into the sleep mode at block 250h.

30 If the detector 50 has to obtain a 30 second sample at block 250l, that sensor count is attained at block 250m and then the detector 50 determines whether to perform a 24 hour smoke test at block 250n. If a 24 hour smoke test is

to be performed, the detector 50 tests the smoke alarm indicator circuitry 124. The process then proceeds to block 250q as further described below.

5 If a 24 hour smoke test is not to be performed at block 250n, the detector determines whether to perform a 10 minute A-to-D test at block 250p. If the detector 50 does not have to perform the 10 minute A-to-D test, the process proceeds to block 250r as further described below.

10 If the A-to-D test is to be performed at block 250p, the detector 50 tests the A-to-D circuitry at block 250q. The detector 50 then checks the carbon monoxide rate of change at block 250r and determines whether to activate the carbon monoxide alarm at block 250s. This determination is independent of the output of the smoke detector circuit U2.

15 If the carbon monoxide alarm detector is to be activated, the detector 50 will determine whether to also activate a smoke alarm at block 250t. If the smoke alarm is not to be activated, the detector 50 will flash the light indicator LED2 of the carbon monoxide alarm indicator circuitry 122 and sound the carbon monoxide horn pattern at block 250u.

20 If the smoke alarm is to be activated at block 250t, the detector 50 will turn off the light indicator LED2 and turn off the carbon monoxide horn pattern. The process will then proceed to block 250x as further described below.

If the carbon monoxide alarm is not to be activated at 250s, the detector 50 will turn off the light indicator LED3 of the carbon monoxide alarm indicator circuitry 122 and the carbon monoxide horn pattern at block 250w. At block 250x, the data will be examined and the detector 50 will determine whether there are any faults at block 250y.

25 If there are no faults, the detector unit 50 will go into the sleep mode at block 250h. If faults are detected at block 250y, the detector 50 will determine whether the carbon monoxide or smoke alarm has been activated at block 250z. If the carbon monoxide or smoke alarm is activated, the processing unit 102 will go into the sleep mode at block 250h. If the carbon monoxide or smoke alarm is not

activated, the detector unit 50 will initiate a trouble chirp at block 250aa and then go into the sleep mode at block 250h.

FIGS. 3 through 12 illustrate detailed flow diagrams of the operations carried out by the detector 50. FIG. 3 illustrates a main routine 300 of the process carried out by the detector 50 to implement various tests, alarm conditions, and smoke and carbon monoxide checks. Initially, the detector unit 50 sets a wake-up time at block 302. The detector unit 50 sets the wake-up time at about 3 seconds for normal mode, about 1.5 seconds for alarm mode, and about .75 seconds for test mode. The detector unit 50 then initializes ports A-C at block 304 and then determines whether a TIME OUT bit has been cleared at block 306. If the TIME OUT bit has been cleared, the process proceeds to the WAKE sub-routine as further described below.

If the TIME OUT bit has not been cleared at block 306, the detector 50 determines whether a POWER DOWN bit has been set at block 312. If the POWER DOWN bit has not been set, the process proceeds to a POWER UP routine as further described below. If the POWER DOWN bit is set at block 312, the detector unit 50 increments a SPECIAL TEST counter at block 314 and then determines whether the SPECIAL TEST counter is greater than 2 at block 316. If the SPECIAL TEST counter is greater than 2, the process proceeds to the WAKE sub-routine. If the SPECIAL TEST counter is not greater than 2 at block 324, the detector unit 50 initializes a TEST counter, sets a START flag at block 318, and then proceeds to a LOOP sub-routine as further described below.

FIG. 4 illustrates a POWERUP sub-routine 320. When the detector 50 is initially turned on, the POWERUP sub-routine initializes various counters, registers, and flags. At block 320a the detector 50 initializes a WAKE UP counter, a SAMPLE counter, and a TEST counter. The detector 50 then clears the registers and flags and sets a START flag a block 320b. The detector 50 then waits about 255 ms at block 320c and sets the ALARM TOGGLE counter CTR equal to 4 at block 320d. The detector 50 clears the ALARM register at block 320e and then it goes into the sleep mode.

FIG. 5 illustrates a WAKE sub-routine 330 that is carried out when the detector 50 is awakened from the sleep mode. At block 330a, the detector 50 determines whether the TEST mode flag is set. If a TEST mode flag is set, the process proceeds to a RESUMET sub-routine 330b. During the RESUMET sub-routine 330b, the detector 50 is kept STARVED (as described above) at block 330c, the yellow light is kept on at block 330d, and the WAKE UP counter is set equal to 1 at block 330e. The detector unit 50 then determines whether the ALARM flag is set at block 330f. If an ALARM flag is set, the process proceeds to a RESET sub-routine as further described below. If the ALARM flag is not set, the process proceeds to a LOOP sub-routine as further described below.

If the TEST mode flag is not set at block 330a, the detector 50 determines whether the ALARM flag is set at block 330c. If the ALARM flag is set, the detector 50 determines whether there is a smoke or carbon monoxide condition at block 330d. If the ALARM flag is not set at block 330c, the detector 50 determines whether the TEST switch is pressed at block 330e. If the TEST switch is not pressed, the process proceeds to a BYE1 sub-routine as further described below.

If the TEST switch is pressed at block 330e, the detector 50 saves the ALARM register at block 330f, sets a TEST flag, sets a WAKEUP counter equal to 1, and turns on the yellow LED4 of the power/low battery indicator circuitry 129 at block 330g. The detector 50 then determines whether the battery level is low at block 330h. If the battery level is not low, the green LED4 of the power/low battery indicator circuitry 129 is turned on at block 330i.

If the battery level of the detector 50 is low at block 330h, the detector turns on the yellow LED at block 330j. The detector then simulates a smoke alarm and turns on the smoke LED3 of the smoke alarm indicator circuitry 124 at block 330k and sound a smoke alarm pattern at block 330l. The detector unit then turns off the smoke LED and simulates the carbon monoxide alarm at block 330m. The detector 50 now turns on the carbon monoxide alarm horn pattern and the LED2 of the carbon monoxide alarm indicator circuitry 122 at

block 330n. Thereafter, the detector 50 turns off the carbon monoxide alarm and the carbon monoxide alarm LED3 at block 330o. The detector will then enter the sleep mode.

FIG. 6 illustrates, a RS1 sub-routine 340. The reset sub-routine 340 is utilized to flash the red and yellow LEDS as CO samples are taken during the test function and sound the alarm when the circuitry has passed the self test. At block 340a, the detector 50 determines whether a QUIET flag is set. If the QUIET flag is set, the detector 50 turns off a BEEPER at block 340b, reloads a TOGGLE register at block 340c, and turns off the red LED2 and yellow LED3 at block 340d.

If the QUIET flag is not set at block 340a, the detector 50 decrements the TOGGLE register at block 340e and then determines whether the TOGGLE register is equal to zero at block 340f. If the TOGGLE register is equal to zero, the process proceeds to block 340b as described above.

If the TOGGLE register is not equal to zero at block 340f, the detector 50 turns on the BEEPER at block 340g and turns on the red LED2 and yellow LED3 at block 340d. Subsequently, the process proceeds to the BYE1 sub-routine as further described below.

FIG. 7 illustrates a RESET sub-routine 350 and a RESET1 sub-routine 355. The RESET sub-routine and RESET1 sub-routine are utilized to restore registers after a manual test.

When the detector 50 carries out the RESET sub-routine 350, it restores the ALARM value at block 350a, reloads the WAKEUP counter at block 350b, and calls CLRREG at block 350c. The process then proceeds to a SHOW sub-routine as further described below.

When the detector 50 carries out the RESET1 sub-routine 355, it reloads the wake-up counter at block 350b and calls CLRREG at block 250c. The process then proceeds to the SHOW sub-routine.

Referring now to FIG. 8 illustrates a LOOP sub-routine 360. The LOOP sub-routine is utilized to determine if the CO alarm flag is set during a test, or if more samples must be taken.

At block 360a, the detector unit 50 retrieves the TIME and then determines whether the carbon monoxide ALARM flag is set at block 360b. If the carbon monoxide ALARM flag is set, the process proceeds to a LOOP2 sub-routine as further described below.

5 If the carbon monoxide ALARM flag is not set at block 360b, the detector determines whether the TEST flag is set at block 360c. If the TEST flag is set, the process proceeds to the LOOP2 sub-routine.

10 If the TEST flag is not set at block 360c, the detector decrements the TEST counter at block 360d and then determines whether the TEST counter is equal to zero at block 360e. If the TEST counter is not equal to zero, the process proceeds to the LOOP2 sub-routine. If the TEST counter is equal to zero, the process proceeds to the TEST sub-routine as further described below.

15 FIG. 9 illustrates a NEG1 sub-routine 370 to carry out a reduction in the counts value to clear an alarm condition if the CO level is decreasing. At block 370a, the detector 50 clears the DIRECTION flag and the subtracts a REDCT value from an ALARM register at block 370b. At block 370c, the detector 50 determines whether the carbon monoxide ALARM is negative.

20 If the carbon monoxide ALARM is not negative, the process proceeds to block 370d as further described below. If the carbon monoxide ALARM is negative at block 370c, the detector clears the carbon monoxide ALARM at block 370e and then determines whether an ALARM value is less than an ALROFF value at block 370d. If the ALARM is less than ALROFF, then the detector 50 clears the carbon monoxide ALARM at block 370f.

25 If the ALARM value is not greater than the ALROFF value at block 370d, the detector 50 decrements a NEGATIVE READING counter at block 370g. If the NEGATIVE READING counter is equal to zero, the detector unit calls CLRREG and the process proceed to the SHOW sub-routine. If the NEGATIVE READING counter is not equal to zero, the process proceeds correctly to the SHOW sub-routine.

FIG. 10 illustrates a TESTR sub-routine 380. The TESTR sub-routine 380 is utilized when the test switch is pressed by a user.

At block 380a, the detector unit 50 determines whether the test switch is pressed. If the test switch is not pressed, the process proceeds to the RES1 sub-routine 340 as described above. If the TEST SWITCH is pressed at 380a, the detector 50 determines whether the unit is in a smoke alarm condition at block 380b.

If the detector 50 is not in a smoke alarm condition at block 380b, it activates the carbon monoxide ALARM at block 380c, sets a four minute delay at block 380d, sets a QUIET carbon monoxide flag at block 380e, turns off the carbon monoxide ALARM at block 380f, sets a counter at block 380g, and decrements the counter at block 380h. At block 380i, the detector 50 determines whether the counter has timed out. If the counter has not timed out, the process proceeds to block 380h. If the counter has time out at block 380i, the detector 50 clears the QUIET flag at block 380j and turns on the carbon monoxide ALARM at block 380k. The process then returns to the beginning of the TESTR sub-routine 380.

If the detector 50 is in a smoke alarm condition at block 380b, it sets an eight minute delay at block 380l, sets a QUIET smoke flag at block 380m, turns off the smoke alarm at block 380n, sets a counter at block 380o, and decrements the counter at block 380p. The detector 50 determines whether the smoke is increasing at block 380g.

If the smoke is increasing, the detector activates the smoke alarm at block 380r and the process proceeds to the beginning of the TESTR sub-routine 380. If the smoke is not increasing at block 380g, the detector 50 determines whether the counter has timed out at block 380s.

If the counter has not timed out, the process proceeds to block 380p. If the counter has timed out at block 380s, the detector 50 clears the QUIET flag at block 380f and activates the smoke alarm at block 380r. The process then proceeds to the beginning of the TESTR sub-routine 380.

FIG. 11 illustrates a SMOKE CHECK sub-routine 390. The SMOKE CHECK sub-routine determines whether the smoke sensor has detected the presence of smoke in the atmosphere and initiates a smoke alarm.

At block 390a, the detector 50 clears a ten minute SMOKE flag.
5 The detector 50 then determines whether a smoke test is in progress at block 390b.

If the smoke test is in progress, the process proceeds to a SMK-TEST sub-routine as further described below. If the detector 50 is not to carry out a smoke test, it checks a smoke feedback pin of the sensor at block 390c. The detector unit then determines whether smoke is present in the atmosphere at block
10 390d.

If smoke is not present, the detector 50 determines whether there has been a smoke glitch at block 390e. If there has been a smoke glitch, the process proceeds to block 390b. If there is not smoke glitch at block 390e, the detector 50 clears the smoke at block 390d and returns to the beginning of the
15 SMOKE CHECK sub-routine 390.

If the detector unit 50 determines that smoke is present at block 390d, it continues processing at block 390f. The detector 50 then determines whether it is in a silence mode at block 390g. If the detector unit 50 is in the hush mode, the process proceeds to a SMOKE PRIORITY sub-routine as further
20 described below.

If the detector 50 is not in the silence mode at block 390g, it the detector unit 500 sets a SMOKE flag at block 390h and then determines whether to execute a Canadian horn pattern at block 390i. One of the advantages of the detector 50 is its ability to store a plurality of horn patterns and use one or more
25 selected patterns.

If the Canadian horn pattern is implemented by the detector 50 at block 390i, it turns on the smoke LED3 at block 390j and turns on the SMOKE BEEPER at block 390k. The process then returns to the beginning of the SMOKE CHECK sub-routine.

If the Canadian horn pattern is to be executed at block 390i, the detector 50 will turn on the smoke LED3 at block 390l and will turn on the Canadian smoke beeper at block 390m. The process then returns to the beginning of the SMOKE CHECK sub-routine 390.

5 FIG. 12 illustrates a TEST sub-routine 400 to test smoke sensor functioning. Initially, the detector 50 clears an ERROR flag and LOW TEMP flag at block 400a, saves all the data at block 400b, sets up a test current at block 400c, and calls an TIME1 at block 400d. The detector 50 then determines whether the sensor output is less than a BOTLIM value at block 400e. If the sensor output is less than the BOTLIM value, the detector 50 sets an ERROR flag at block 400f and the process proceeds to block 400h as further described below.

10 If the sensor output is not less than the BOTLIM value at block 400e, the detector 50 determines whether the sensor output is greater than a TOPLIM value at block 400g. If the sensor output is less than the TOPLIM value, the detector 50 sets the ERROR flag at block 400f and the process proceeds to block 400h. If the sensor output is not less than the TOPLIM value at block 400g, the detector 50 determines whether an ALARM is greater than zero at block 400h.

15 If the ALARM is not greater than zero at block 400h, the detector 50 subtracts a REDMIN value from the ALARM register at block 400i and then determines whether the ALARM register is negative at block 400j. If the ALARM register is negative, the detector 50 sets the ALARM register equal to zero at block 400k and the process proceeds to block 400l as further described below. If the ALARM register is not negative at block 400j, the process proceeds to block 400l.

20 If the ALARM is greater than zero at block 400h, the detector 50 turns on the thermistor at block 400l, calls TIME1 at block 400m, and clears a LOW TEMP flag at block 400n. The detector 50 then determines whether a HIGH BYTE value is greater than REF value at block 400o.

 If the HIGH BYTE value is not greater than REF value, the detector restores the saved data at block 400p, and initializes the WAKEUP counter and

restores the TEST counter at block 400q. The process then proceeds to the BAT1 sub-routine as further described below.

5 If the HIGH BYTE value is greater than the REF value at block 400o, the detector 500 sets the LOW TEMP flag at 400r, restores the saved data at block 400p, initializes the WAKEUP counter, and restores the TEST counter at block 400q. The process then proceeds to the BAT1 sub-routine.

10 Referring now to FIG. 13, a block diagram of another embodiment of a detector 500 is illustrated. The detector 500 is a battery powered, single station, self-contained carbon monoxide alarm. The detector 500 detects the presence and concentration of carbon monoxide in the atmosphere and provides a warning of potential hazardous carbon monoxide conditions. The detector 500 corresponds in many respects in construction and function to the previously described detector 50 except that the detector 500 does not detect the presence of smoke. The component of the detector 500 generally corresponding to those
15 components of the detector unit 50 are designated by like-reference numerals in the six-hundred series. As shown in FIG. 14, the central processing unit 602 includes a microchip PIC16C58A, available from microchip.

20 FIG. 15 illustrates a flow diagram of the general operations carried out by the detector 500. The detector monitors the carbon monoxide in the atmosphere and sounds an alarm if a hazard condition is present.

After the detector 500 is awakened at block 800a or powered up at block 800b, the detector initializes a watchdog timer and initializes one or more ports at block 800c. At block 800d, the detector 500 determines whether the unit was just powered up. If the detector 500 was just powered up, the detector
25 implements a power-up delay at block 800e, and then initializes one or more counters, clears one or more sample registers, clears one or more flag registers, and clears an alarm register at block 800f. The detector 500 then obtains an initial sensor count at block 800g and then the detector 500 is put in the sleep mode at block 800h.

If the detector 500 was not recently powered up at block 800d, the detector 500 determines whether to implement a manual test at block 800i. If the manual test is to be implemented, the detector 500 performs the manual test at block 800j and then the detector 500 is put in the sleep mode at block 800h.

5 If a manual test is not to be performed at block 800i, the detector 500 determines whether to obtain a 30 second sample at block 800k. If the detector 500 is not to obtain a sample, the detector 500 will be put in the sleep mode at block 800h.

10 If the detector 500 is to obtain a 30 second sample at block 800k, the detector 500 obtains a sensor count at block 800l and then determines whether to perform a 10 minute A-to-D test at block 800m. If the detector 500 is not to perform the A-to-D test, the process proceeds to block 800o.

15 If the detector 500 is to perform the 10 minute A-to-D test at block 800m, the detector 500 tests the A-to-D circuitry at block 800n and then checks the carbon monoxide rate of change at block 800o.

20 At block 800p, the detector 500 determines whether to activate the carbon monoxide alarm. If the carbon monoxide alarm is to be activated, the detector 50 flashes the light indicator LED2 of the carbon monoxide indicator circuitry 622 (see FIG 15) and sounds the carbon monoxide horn pattern at 800q. The process then proceeds to block 800s as further described below.

 If the carbon monoxide alarm is not to be activated at block 800p, the detector 50 turns off the carbon monoxide LED2 and horn at block 800r, and shows data at block 800s.

25 At block 800t, the detect or 500 determines whether there are any faults at block 800t. If there are not any faults at block 800t, the detector 500 is put in the sleep mode at block 800w.

30 If there are faults, the detector 500 determines whether to check the carbon monoxide alarm at block 800u. If the carbon monoxide is to be checked, the detector 500 is put in the sleep mode at block 800w. If there is no problem with the carbon monoxide alarm is not to be checked, the detector 500 generates a

trouble chirp at block 800v and then the detector is put into the sleep mode at block 800w.

FIG. 16 shows a flow diagram of a main program carried out by the detector 500. At block 810a, the detector 500 sets a wake-up time (i.e., about 3
5 seconds for normal mode and about 1.5 seconds for alarm mode). The detector 500 then initializes ports A and B at block 810b and determines whether a TIME OUT bit is cleared at block 810c. If the TIME OUT bit is cleared, the detector 500 proceeds to a WAKE sub-routine as further described below.

If the TIME OUT bit is not cleared at block 810c, the process
10 proceeds to a POWER UP sub-routine as further described below. The detector 500 then waits about 300 ms at block 810d. At block 810e, the detector 500 initializes a WAKE UP counter, a SAMPLE counter, and a TEST counter at block 810e. The detector 500 then clears one or more registers and flags at block 810f, clears an ALARM REGISTER at block 810g, sets a START flag at block 810h,
15 and then goes into the sleep mode.

Referring now to FIG. 17, a WAKE sub-routine 820 is illustrated. The WAKE sub-routine is performed when the processor is awakened from the sleep mode.

At block 820a, the detector 500 determines whether a TEST MODE
20 flag is set. If the TEST MODE flag is set, the process will proceed to a RESUMET sub-routine 820b. While carrying out the steps of the RESUMET sub-routine 820b, the detector 500 is kept STARVED at block 820c and a WAKEUP counter is set equal to 1 at block 820d. The detector 500 then determines whether the ALARM flag is set at block 820e. If the ALARM flag is set, the process proceeds
25 to a RESET sub-routine as further described below. If the ALARM flag is not set at block 820e, the process proceeds to a LOOP sub-routine as further described below.

If the TEST MODE flag is not set at block 820a, the detector 500 determines whether an ALARM flag is set at block 820f. If the ALARM flag is
30 set, the process proceeds to a TESTR sub-routine as further described below.

If the ALARM flag is set at block 820f, the detector 500 determines whether a test switch is pressed at block 820g. If the test switch is not pressed, the process proceeds to a BYE1 sub-routine as further described below.

5 If the test switch is pressed at block 820g, the detector 500 determines whether an error flag is set at block 820h. If the error flag is set, the process proceeds to a RESERR sub-routine as further described below.

10 If the error flag is not set at block 820h, the detector saves the data in an ALARM register at block 820i, sets a TEST flag and sets the WAKEUP counter equal to 1 at block 820j. Thereafter, the detector 500 turns on the yellow LED1 at block 820k, waits 100 ms at block 820l, turns off the yellow LED1 at block 820m, and clears a START flag at 820n. The process will then proceed to a BEEPX sub-routine as further described below.

15 FIG. 18 illustrates a BY1 sub-routine 840 and the TESTR sub-routine 830. The TESTR sub-routine 830 is utilized to determine if the test switch is being pressed during an alarm to silence the unit and the BYE1 sub-routine is utilized to decrement the WAKEUP counter to determine what WAKEUP routine to accomplish.

20 At block 830a, the detector 500 determines whether the test switch is pressed. If the test switch is not pressed, the process proceeds to an ALR1 sub-routine as further described below. If the test switch is pressed at block 830a, the detector 500 determines whether a QUIET INHIBIT flag is set at block 830b. If the QUIET INHIBIT flag is set, the process proceeds to block 830g as further described below.

25 If the QUIET INHIBIT flag is not set at block 830b, the detector 500 sets a 4 minute delay at block 830c, sets a QUIET ONCE flag at block 830d, sets a QUIET flag at block 830e, turns off the beeper at block 830f, waits for a switch release at block 830g, and then decrements the WAKEUP counter at block 830h. The detector 500 then determines whether the WAKEUP counter is equal to zero at block 830i. If the WAKEUP counter is not equal to zero, the detector 500
30 is put into the sleep mode.

If the WAKEUP counter is equal to zero at block 830i, the WAKEUP counter is reloaded (i.e., the WAKEUP counter is set to 10 for normal mode and equal to 20 for alarm mode) at block 830j. At block 830h, the detector 500 determines whether the ALARM flag is set. If the ALARM flag is not set, the process proceeds to a LOOP sub-routine as further described below.

If the ALARM flag is set at block 830h, the detector 500 decrements the TEST counter at block 830l, and the process proceeds to a LOOP sub-routine. If the TEST counter is equal to zero at block 830l, the detector 500 clears the QUIET flag at block 830m and the process proceeds to the LOOP sub-routine.

Referring now to FIG. 19, a flow diagram of the ALR1 sub-routine 840 is illustrated. The ALR1 sub-routine 840 is utilized to activate the carbon monoxide LED2 and horn.

At block 840a, a TEST ALARM counter is set equal to 2 and an ALARM COUNTER is set equal to 3. At block 840b, the detector determines whether the QUIET flag is set. If the QUIET flag is set, the process proceeds to block 840d as further described below.

If the QUIET flag is not set at block 840b, the detector 500 turns on the horn at block 840e, turns on the carbon monoxide LED2 at block 840d, waits 100 ms at block 840e, turns off the carbon monoxide LED2 at block 840f, waits about 400 ms at block 840g, decrements the ALARM counter at block 840h, and then determines whether the ALARM counter is equal to zero at block 840i. If the alarm counter is not equal to zero, the process proceeds to block 840b.

If the alarm counter is equal to zero at block 840i, the detector 500 turns off the horn at block 840j and then determines whether a TEST flag is set at block 840k. If the TEST flag is set, the detector 500 decrements the test alarm counter by 1 at block 840l and then determines whether the test alarm counter is equal to zero at block 840m.

If the test alarm counter is equal to zero, the process proceeds to a RESET sub-routine as further described below. If the test alarm counter is not equal to zero at block 840m, the detector will be put into the sleep mode.

5 If the TEST flag is set not at block 840k, the detector 500 will decrement the WAKEUP counter by 1 at block 840n and then the detector 500 determines whether the WAKEUP counter is equal to zero at block 840o. If the WAKEUP counter is not equal to zero, the detector 500 is put into the sleep mode.

10 If the WAKEUP counter is equal to zero at block 840o, the detector 500 reloads the WAKEUP counter with a ALARM DIV value at block 840p. The process then proceeds to a sub-routine MIN4 as further described below.

15 FIG. 20 illustrates the RESET sub-routine 850 and a RESET1 sub-routine 852 of the main routine. At block 850a, the detector 500 restores the ALARM value. The detector 500 then reloads the WAKEUP counter at block 850b and then calls CLRREG at block 850c. The process then proceeds to ALRH X sub-routine as further described below.

20 Referring now to FIG. 21, the LOOP sub-routine 860 is illustrated. The LOOP sub-routine 860 is implemented to determine if a manual self test needs to be performed. At block 860a, the detector 500 calls TIME and then determines whether an ALARM flag is set at block 860b. If the ALARM flag is set, the process proceeds to a LOOP2 sub-routine as further described below.

25 If the ALARM flag is not set at block 860b, the detector 500 determines whether the TEST flag is set at block 860c. If the TEST flag is set, the process proceeds to the LOOP2 sub-routine. If the TEST flag is not set at block 860c, the detector 500 decrements the TEST counter at block 860d and then determines whether the TEST counter is equal to zero at block 860e. If the TEST counter is not equal to zero, the process proceeds to the LOOP2 sub-routine. If the TEST counter is equal to zero at block 860e, the process proceeds to a TEST sub-routine as further described below.

30 FIG. 22 illustrates a NEG1 sub-routine to a reduction in the counts value to clear an alarm condition if the CO level is decreasing. At block 870a, the

detector 500 clears a DIRECTION flag and subtracts a REDCT value from the ALARM register at block 870b. The detector 500 then determines whether the ALARM register is negative at block 870c. If the ALARM is not negative, the process proceeds to block 870d as further described below. If the ALARM is negative at block 870c, the detector 500 clears the ALARM register at block 870e and then determines whether the ALARM is less than an ALROFF value at block 870d. If the ALARM register is less than the ALROFF value, the detector clears the ALARM register at block 870f.

10 If the ALARM register is not less than the ALROFF value at block 870d, the detector 500 decrements a NEGATIVE READING counter at block 870g. If the NEGATIVE READING counter is not equal to zero, the process proceeds to the SHOW sub-routine as further described below. If the NEGATIVE READING counter is equal to zero, the detector 500 calls CLRREG at block 870h. The process then proceeds to the SHOW sub-routine.

15 Referring now to FIG. 23, the TEST sub-routine 880 is illustrated. The TEST sub-routine 880 is utilized to test and exercise the carbon monoxide sensing electronics, while maintaining the previous samples and data acquired.

Initially, the detector 500 clears an ERROR flag at block 880a, saves all the data at block 880b, sets up a test current at block 880c, calls TIME1 at 20 block 880d, and determines whether the sensor output is less than a BOTLIM value at block 880e.

If the sensor output is less than the BOTLIM value, the detector 500 sets an ERROR flag at block 880f, and then the process proceeds to block 880g as further described below. If the sensor output is not less than the BOTLIM value at block 880e, the detector 500 determines whether the sensor output is less 25 than a TOPLIM value at block 880h.

If the sensor output is less than the TOPLIM value, the detector 500 sets an ERROR flag at block 880f, and the process proceeds to block 880g. If the sensor output is not less than the TOPLIM value at block 880h, the detector 500 30 determines whether the ALARM register is equal to zero at block 880g.

If the ALARM register is not equal to zero at block 880g, the detector 500 subtracts a REDMIN register from the ALARM register at block 880i, and then determines whether the ALARM register is negative at block 880j. If the ALARM register is not negative, the process proceed to block 880l as further described below. If the ALARM register is negative at block 880j, the detector 500 sets the ALARM register equal to zero at block 880k and then the process proceeds to block 880l as further described below.

If the ALARM register is equal to zero at block 880g, the detector 500 will restore the save data at block 880l. The detector 500 will then initialize the WAKEUP counter and restore the TEST counter at block 880m. The process then proceeds to the BAT1 sub-routine as further described below.

FIG. 24 illustrates the BAT1 sub-routine 890 and a Loop2 sub-routine 900. The BAT1 sub-routine 890 determines whether the battery of the detector 500 is at a sufficient voltage level and the LOOP2 sub-routine turns off the IR LED and power LED after a sample has been taken and stores the current sample value.

The detector 500 turns on the IR LED of the carbon monoxide sensor at block 890a and decrements a ALARM TOGGLE register at block 890b. If the ALARM TOGGLE is equal to zero at block 890b, the detector is put into the sleep mode with their LED on. If the ALARM TOGGLE is not equal to zero at block 890b, the detector 500 clears a LOW BATTERY flag at block 890c, turns on the red LED2 at block 890d, waits about 10 ms at block 890e, and then determines whether the battery line is at a low level at block 890f.

If the battery line is not at a low voltage level, the process proceeds to block 890g as further described below. If the battery line is at a low level at block 890f, the detector 500 sets a LOW BATTERY flag at block 890h, turns off their LED at block 890g, turns off the red LED at block 890i, and then determines whether a START flag has been set at block 890k.

If the START flag is not set, the process proceeds to a INSPECT sub-routine as further described below. If the START flag is set at block 890k, the

detector unit 500 copies a current sample to a last sample buffer at block 890l, clears the START flag at block 890m, and then the process proceeds to the INSPECT sub-routine.

FIG. 25 illustrates the INSPECT sub-routine 910. The INSPECT sub-routine 910 is utilized to evaluate the difference between the previous sample and the present sample.

At block 910a, the detector 500 determines whether a HIGH BYTE is greater than an HFAULT value. If the HIGH BYTE is not greater than the HFAULT value, the process proceeds to block 910b as further described below. If the HIGH BYTE is greater than the HFAULT value at block 910a, the detector 500 sets an ERROR flag at block 910c and then determines whether the HIGH BYTE is greater than a HIVAL1 value at block 910b.

If the HIGH BYTE is greater than the HIVAL1 value, the process proceeds to block 910e as further described below. If the HIGH BYTE is not greater than the HIVAL1 value at block 910b, the detector 500 sets the ERROR flag at block 910d, saves a previous sample in registers A and B at block 910e, and then determines whether the TEST flag is set at block 910f.

If the TEST flag is set, the process proceeds to block 910g as further described below. If the TEST flag is not set at block 910f, the detector 500 moves the current sample to the last sample register at block 910h, calculates the difference between the current sample and the last sample at block 910g, and then determines whether the difference is negative at block 910i.

If the difference is negative, the process proceeds to the NEG1 sub-routine as described above. If the difference is not negative at block 910i, the process proceeds to a POS1 sub-routine as further described below.

FIG. 26 illustrates the POS1 sub-routine 920 to determine if we are in a high level alarm and a ACC3 sub-routine 922 to add the equate for the previous sample to the alarm register. At block 920a, the detector 500 determines whether a HIGH BYTE is equal to zero. If the HIGH BYTE is not equal to zero, the process proceeds to a ADJ1 sub-routine 924 as further described below. If the

HIGH BYTE is equal to zero, the detector 500 determines whether a LOW BYTE is equal to zero at block 920b.

5 If the LOW BYTE is not equal to zero, the detector 500 sets a DIRECTION flag at block 920c and the process proceeds to block 920d as further described below. If the LOW BYTE is equal to zero at block 920b, the detector 500 determines whether the LOW BYTE is greater than a SUPRL value at block 920d.

10 If the LOW BYTE is greater than the SUPRL value, the process proceeds to the ADJ1 sub-routine 924 as further described below. If the LOW BYTE is not greater than SUPRL at block 920d, the detector 500 assigns the difference to the current sample register at block 920e, decrements a sample register pointer and reloads the register pointer to five when the sample register pointer is equal to zero at block 920f. The detector 500 adds the five sample registers and stores the result in a SUMREG register at block 920g. The process
15 then proceeds to a ACCUM sub-routine as further described below.

During the ACC3 sub-routine 922, the detector 500 adds the difference to the ALARM register at block 922a, and then determines whether the ALARM register exceeds 255 at block 922b. If the ALARM register does not
20 exceed 255, the process proceeds to a CHKRDH sub-routine as further described below. If the ALARM register exceeds 255 at block 922b, the process proceeds to the ADJ1 sub-routine 924.

During the ADJ1 sub-routine 924, the detector unit 500 determines whether the ALARM is equal to 255 and sets an ALARM flag at block 924a. The detector 500 then sets up an ALARM TOGGLE at block 924b and determines
25 whether the QUIET flag is set at block 924c.

If the QUIET flag is set, the process proceeds to the SHOW sub-routine as further described below. If the QUIET flag is not set at block 924c, the detector 500 determines whether the TEST flag is set at block 924d.

30 If the TEST flag is not set, the process proceeds to the SHOW sub-routine. If the TEST flag is set at block 924d, the detector 500 turns on the red

LED and turns on the beeper at block 924e. The process then proceeds to the SHOW sub-routine.

FIG. 27 illustrates the ACCUM sub-routine 930 and a SET6 sub-routine. The ACCUM sub-routine 930 is utilized to determine what value to assign to the lower byte of the sum register, and the SET6 sub-routine is implemented to assign the sum 6 value to the low byte of the sum register.

At block 930a, the detector 500 obtains a SUMREGL value and then determines whether a TEST flag is set at block 930b. If the TEST flag is set, the process proceeds to a ACC4 sub-routine as further described below. If the TEST flag is not set at block 930b, the detector unit 500 determines whether a DIRECTION flag is set at block 930c.

If the DIRECTION flag is not set, the process proceeds to block 930d as further described below. If the DIRECTION flag is set at block 930c, the detector unit 500 determines if an ALARM flag is set at block 930e.

If the ALARM flag is not set, the process proceeds to block 930d. If the ALARM flag is set at block 930e, the detector 500 reloads the NEGATIVE counter at block 930f.

At block 930d, the detector 500 determines whether a SUMREGH value is equal to zero. If the SUMREGH value is not equal to zero, the process proceeds to a SET6 sub-routine 930. If the SUMREGH is equal to zero at block 930d, the detector unit 500 determines whether the SUMREGL value is equal to zero at block 930g.

If the SUMREGL value is equal to zero, the process proceeds to a CHKSP sub-routine as further described below. If the SUMREGL is not equal to zero at block 930g, the detector 500 determines whether a LOW TEMP flag is set at block 930h.

If the LOW TEMP flag is set at block 930h, the detector 500 determines whether the SUMREGL value is less than 3 at block 930i. If the SUMREGL value is less than three, the detector 500 sets the SUMREGL value equal to three at block 930j, and will times the SUMREGL by two at block 930k,

and the process proceeds to block 930l. If the SUMREGL is not less than 3 at block 930i, the detector unit 500 times the SUMREGL by two at block 930k, and the process proceeds to block 930l.

Now, the detector unit 500 compares the SUMREGL to LEVEL1
 5 through LEVEL5 values. If the SUMREGL is less than the LEVEL1 value, the detector unit 500 sets the SUMREGL value equal to a SUM1 value at block 930m. If the SUMREGL value is less than the LEVEL2 value at block 930n, the detector 500 sets the SUMREGL value equal to a SUM2 value at block 930o. If the SUMREGL value is less than the LEVEL3 value at block 930p, the detector 500
 10 sets SUMREGL value equal to a SUM3 value at block 930q. If the SUMREGL value is less than the LEVEL4 value at block 930r, the detector 500 sets the SUMREGL value equal to a SUM4 value at block 930t. If the SUMREGL value is less than a LEVEL5 value at block 930v, the detector 500 sets the SUMREGL value equal to a SUM5 value at block 930w.

15 If the detector 500 has set the SUMREGL value equal to the SUM1 value, SUM2 value, the SUM3 value, the SUM4 value, or the SUM5, value the process proceeds to the ACC3 sub-routine as further described below. If the SUMREGL is not set to one of these values, the process proceeds to the SET6 sub-routine 930. Subsequently, the detector 500 sets the SUMREGL equal to SUM6 at
 20 block 930a. The process then proceeds to the ACC3 sub-routine as further described below.

FIG. 28 illustrates the CHKSP sub-routine 940 and CHKRDH sub-routine 950. The CHKSP sub-routine 940 is utilized to check if the present sample is at a flat level or if it has changed direction from the previous sample.

25 At block 940a, the detector unit 500 determines whether a DIRECTION flag is set. If the DIRECTION flag is not set, the process proceeds to the CHKRDH sub-routine 950. If the DIRECTION flag is set at block 940a, the detector 500 determines whether a ALARM counter is greater than a FLATLVL value at block 940b.

If the ALARM counter is not greater than the FLATLVL counter, the process proceeds to the CHKRDH sub-routine 950. If the ALARM counter is greater than the FLATLVL value at block 940b, the detector 500 adds the FLATLVL value to a SUMREG register at block 940g, and the process proceeds to an ACC3 sub-routine as further described below.

The CHKRDH sub-routine 950 is utilized to determine the status of the sensor high flag. At block 950a, the detector determines whether a SENSOR HIGH flag is set at block 950a. If the SENSOR HIGH flag is not set, the process proceeds to the SHOW sub-routine as further described below. If the SENSOR HIGH flag is set at block 950a, the process proceeds to a ADJ1 sub-routine as further described below.

FIG. 29 illustrates a flow diagram of the SHOW sub-routine 960 and a NOSHOW sub-routine 965. The SHOW sub-routine 960 is utilized to present the data stream through RS-237 communication to peripherals and the power LED.

At block 960a, the detector 500 determines whether an EOL line is at a low level. If the EOL line is at a low level, the process proceeds to a NOSHOW sub-routine 965 as described below. If the EOL line is not at a low level at block 960a, the detector 500 switches a SERIAL line to an output at block 960b.

At block 960c, the detector 500 clears a SYNC bit, waits for a predetermined amount of time, and sets the SYNC bit. The detector 500 then sets an REGC register equal to the last register plus 1 at block 960d, decrements the REGC register at block 960e, and then determines whether the REGC register is equal to zero at block 960f.

If the REGC register is not equal to zero, the detector obtains the data pointed to by the REGC register and then the process proceeds to an XMITR sub-routine as further described below. If the REGC is equal to zero at block 960f, the process proceeds to the NOSHOW sub-routine 965.

The NOSHOW sub-routine 965 is utilized to determine if there is a low battery, error or power up flag set and sound the correct horn pattern. At block 965a, the detector 500 determines whether an ALARM flag is set. If the ALARM flag is set, the process proceeds to block 965b as further described below. If the
5 ALARM flag is not set at block 965a, the detector 500 determines whether an ERROR flag is set at block 965c.

If the ERROR flag is set, the detector 500 issues a double beep at block 965d, and the process proceeds to block 965b as further described below. If the ERROR flag is not set at block 965c, the detector unit determines whether a
10 LOW BATTERY flag is set at block 965e.

If the LOW BATTERY flag is set, the detector 500 issues a single beep at block 965f. If the LOW BATTERY flag is not set at block 965e, the detector determines whether a START flag is set at block 965g.

If the START flag is set, the detector 500 issues a welcome wake-up
15 chirp at block 965h. If the START flag is not set at block 965g, the detector 500 clears the START flag at block 965b and the detector 500 is put into the sleep mode.

FIG. 30 illustrates the XMTR sub-routine 970 to synchronize the data stream. At block 970a, a REGC register is loaded with 8. The detector 500
20 then rotates the value of a REGA register into a CARRY bit at block 970b and then determines whether the CARRY bit is set at block 970c.

If the CARRY bit is set, the process proceeds to block 970d as further described below. If the CARRY bit is not set at block 970c, the detector 500 sets a TRANSMIT bit at block 970e and then determines whether the CARRY
25 bit is cleared at block 970d.

If the CARRY bit is cleared, the process proceeds to block 970f as further described below. If the CARRY bit is not cleared at block 970d, the detector 500 clears the TRANSMIT bit at block 970g, waits a predetermined amount of time at block 970f, clears a SYNC bit at block 970h, waits another
30 predetermined amount of time at block 970i, sets the SYNC bit at block 970j, and

decrements a REGC register at block 970k. The process then proceeds to block 970b unless the REGC register is equal to zero. If the REGC register is equal to zero at block 970k, the detector 500 sets the TRANSMIT bit at block 970l, and byte has been sent, continue.

5 FIG. 31 illustrates the TIME sub-routine 975 and the TIME1 sub-routine 977. The TIME and TIME1 sub-routines are utilized to take a carbon monoxide sample.

10 At block 975a, the detector unit 500 turns on the IR LED, sets a TRIS register to remove capacitor discharge, removes test current source, and enables the photo diode power source. At block 975b, the detector 500 clears the time counters, a RTCC bit, and an OVERFLOW flag. The detector 500 then increments the time counters at block 975c, and then determines whether the time counter equals an overflow value at block 975d.

15 If the time counter is equal to the overflow value, the detector 500 sets an overflow flag and sets counters to FFFF at block 975e. The process then proceeds to block 975g as further described below. If the time counter is not equal to the overflow value at block 975d, the detector 500 determines whether the RTCC should be incremented at block 975f.

20 If the RTCC should not be incremented, the process proceeds to block 975c. If the RTCC is to be incremented at block 975f, the detector 500 will turn off the IR LED, disable the photo diode power source, and restore the capacitor discharge at block 975g. The process then will proceed to the beginning of the TIME sub-routine 975 or TIME1 sub-routine 977.

25 FIG. 32 illustrates a DEL001 sub-routine 980. The DEL001 sub-routine 980 is utilized as a fixed time delay for the microcontroller timing. At block 980a, the detector 500 loads a REGB register with 71H, NOP at block 980b, decrements the REGB register at block 980c, and then determines whether the REGB register is equal to zero at block 980d.

The process will proceed to block 980b unless the REGB register is equal to zero. When the REGB register 13 is equal to zero, the process will return to the beginning of the DEL001 sub-routine 980.

FIG. 33 illustrates a DEL255 sub-routine 982 and a DELPROG sub-routine 984 for a fixed timing delay on the microcontroller. At block 982a, the detector 500 loads a TEMP register with FFh. The detector 500 then calls DEL001 at block 982b, decrements the TEMP register at block 982c, and then determines whether the TEMP register is equal to zero at block 982d.

The process proceeds to block 982b unless the TEMP register is equal to zero. When the TEMP register is equal to zero, the process returns to the beginning of the DEL255 sub-routine 982 or the DELPROG sub-routine 984.

FIG. 34 illustrates a CLRREG sub-routine 986. The CLRREG sub-routine 986 is utilized to reset the microcontroller at power-up, and ensure LED's and horn are off.

As shown in FIG. 34, the detector 500 clears one or more SAMPLE registers at block 986a, clears one or more flags at block 986b, sets a START flag at block 986c, and clears Port B at block 986d. The detector 500 then turns off the red LED2 and yellow LED1 at block 986e. The process then returns to the beginning of the CLRREG sub-routine 986.

FIG. 35 shows a M16 sub-routine 988 to add the determined weight to the low byte of the sum register. At block 988a, the detector 500 adds W to the SUMREGL register. The detector 500 then determines whether a CARRIER register is set at block 988b.

If the CARRIER register is not set, the process returns to the beginning of the M16 sub-routine 988. If the CARRIER register is set at block 988b, the detector 500 increments the SUMREG register at block 988c and then the process returns to the beginning of the M16 sub-routine 988.

Although the present invention has been described in detail by way of illustration and example, it should be understood that a wide range of changes and modifications can be made to the preferred embodiments described above

- without departing in any way from the scope and spirit of the invention. Thus, the described embodiments are to be considered in all respects only as illustrative and not restrictive, and the scope of the invention is, therefore, indicated by the appended claims rather than the foregoing description. All changes that come
- 5 within the meaning and range of equivalency of the claims are to be embraced within their scope.

1
2
3
4
5
6
7
8
9
10
11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
2211
2212
2213
2214
2215
2216
2217
2218
22